

# Growatt ShineWiFi-X

- Cable free, easy installation
- USB communication port
- Build-in storage, 1 month data
- Online monitoring and maintenance



P O W E R  
- I N G O  
T O M O -  
R R O W O



[www.ginverter.com](http://www.ginverter.com)

Datasheet		ShineWiFi-X
<b>Wireless Parameters</b>		
Wireless standard	802.11 b/g/n	
Frequency range	2.4G~2.5G (2412M~2484M)	
Transmit power	802.11b: 16±2 dBm (@11Mbps) 802.11g: 14±2 dBm (@54Mbps) 802.11n: 13±2 dBm (@HT20, MCS7)	
Receiver sensitivity	CCK, 1 Mbps : -90dBm CCK, 11 Mbps: -85dBm 6 Mbps (1/2 BPSK): -88dBm 54 Mbps (3/4 64-QAM): -70dBm HT20, MCS7 (65 Mbps, 72.2 Mbps): -67dBm	
<b>Hardware Parameters</b>		
Data interface	USB	
Operation voltage	5V(+/-5%)	
Max.power consumption@transmit	1.2W	
Display	LED	
<b>Application Parameters</b>		
Supported servers	ShineServer	
Inverter communication	USB (Modbus RTU protocol)	
Server communication	TCP (Modbus TCP protocol)	
Max. communication range	50m	
Configure type	APP configure	
Data transfer interval	5 Minutes	
Default server URL	server.growatt.com	
<b>General Data</b>		
Dimensions(L/W/H)	135/79/29 mm	
Weight	60g	
Operating temperature range	-20 °C ~ +65 °C	
Warranty	1 year	
CE		